

Mauro Electric Inc.
Po Box 528
Snohomish, WA 98291
360-653-5300
operations@mauroelectric.com

To shut down the generator and check the oil during a power outage follow these steps:

1. Go out to the generator and lift the lid or access door covering the breaker on the generator.
 2. Turn off the breaker.
 3. Let the generator run for 2-3 minutes with the breaker off.
 4. Push the off button on the controller.
 5. Check the oil and refill oil if needed
 6. Make sure the oil dipstick (fill port and dipstick are colored orange, sometimes these are in the same location) is inserted all the way and the oil fill cap is screwed in and tight.
 7. Make sure nothing is in range of any moving parts and push the auto button on the controller and the generator will start.
 8. Let the generator run and warm up for 2-3 minutes.
 9. Turn on the breaker.
 10. Close the lid and all compartments that were opened.
- These steps are very crucial to follow exactly as written because we do not want the generator to shut down or start up under any load as it will compromise your electrical system and appliances.
 - We recommend doing this procedure every 24 hours during an extended period of use.
 - We also recommend that if power is not needed while you are not at the home or at night when everyone is asleep to shut the generator down by following steps 1-4 and then 7-10 to start the generator back up.
 - If the generator runs for more than two days then you will need to call us to schedule a service when the power is restored or change the oil in the generator until your next scheduled service.



Possible locations for your generator breaker.